

# PA AMPLIFIER AS-250-DP

PA AMPLIFIER  
AS-250-DP



## FEATURES & FACILITIES

- 220-240V AC & 12V DC Operation.
- 6 MIC & 2 AUX input.
- Pre-amplifier & Line output for connection to a booster
- Amplifier and for recording the programme.
- Instant transfer to DC power (Car Battery) if AC Power fails.
- Bass & Treble tone control Cut type
- Line input for connecting the output from any external mixer or preout SSA-300 a Booster to be used as booster power amplifier
- Bass boost defeated at driver unit position for safer operation of driver units.
- Built-IN MP3 Plyer (With remote control), for USB, SD/MMC card Reader, FM & Bluetooth Connectivity.
- Adjustable echo volume.
- 20-250 mili second delay time.

## TECHNICAL SPECIFICATION

|   |  |
|---|--|
| <b>POWER OUTPUT</b>                     | <b>330W RMS @ 10% THD<br/>350 MAX</b>  |
| <b>INPUT CHANNEES</b>                   | <b>6 X MIC 0.65MV/4.7 K ohms<br/>2 X AUX 100 mV/470 K ohms<br/>1 X LINE 1V/50K ohms</b>                                      |
| <b>FREQUENCY RESPONSE</b>               | <b>50- 15000HZ+- 3db</b>   |
| <b>SIGNAL TO NOISE RATIO</b>            | <b>60 db</b>   |
| <b>TONE CONTROLS:</b>                   | <b>BASS +- 10db at 100Hz<br/>TREBLE +- 10db at 100Hz</b>   |
| <b>Preamp output</b>                    | <b>200 mV/600 ohms</b>   |
| <b>Line Output</b>                      | <b>1V/ 1kohms</b>  |
| <b>Output Taps for Speaker Matching</b> | <b>4<math>\Omega</math>, 8<math>\Omega</math> ohms(For Direct<br/>Connection)<br/>70 &amp; 100V: Line (For use with LMT)</b> |
| <b>Power Supply</b>                     | <b>AC : 220-240 Volts 50/60 Hz<br/>DC: 12V</b>   |
| <b>AC POWER CONSUMPTION</b>             | <b>460 VA</b>  |
| <b>DC POWER CONSUMPTION</b>             | <b>6 A</b>   |
| <b>ECHO DELAY TIME</b>                  | <b>30-25 MILI SECOND</b>   |
| <b>NET WT</b>                           | <b>14.500 KG Approx</b>  |
| <b>Dimensions</b>                       | <b>W- 430 x H-130 x D-280 (Approx)</b>   |