ASES SECURITY PVT. LTD.
AN ISO 9001:2015 CERTIFIED COMPANY
CIN: U32109DL 2006PTC156438

सबसे पहले भारत India First

PA AMPLIFIER AS-100-DP

PA AMPLIFIER
AS-100-DP



FEATURES & FACILITIES

- 220-240V AC & 12V DC Operation.
- 5 MIC & 2 AUX input.
- Pre amplifier & Line Output for connecting to a Booster Amplifier and for recording the Programme.
- Instant transfer to DC power (Car Battery) if AC power fails.
- Built in MP3 plyer with Remote Control for Bluetooth, USB, MMC/SD & FM Plyer
- Delay & Repeat effects in all 5 Mics
- Bass & Treble Cut Boost type.

HEAD OFFICE: 301, Aggarwal Tower, L.S.C.-II, Mandawali, Patparganj, Delhi-110092.
OFFICE & WORKS : ASES House, A-2/69, Site-IV, Sahibabad Industrial Area, Ghaziabad, U.P. -201010.
•Delhi •Ghaziabad (UP) •Mumbai •Kolkata •Banglore
marcom@asesindia.com
011-22776729, 0120-4152341
www.asesindia.com

TECHNICAL SPECIFICATION

POWER OUTPUT	125 W Max. 100W RMS @ 10% THD
INPUT CHANNELS	5 x MIC 0.60mV/4.7kΩ 2 x AUX 100mV/470kΩ
FREQUENCY RESPONSE	50-15000Hz ±3dB
SIGNAL TO NOISE RATIO	60dB
TONE CONTROLS	Bass ±10db at 100Hz Treble ±10db at 10kHz
Preamp output Line Output	200 mV/600Ω 1V/ 1kΩ
SPEAKER OUTOUT	4Ω,8Ω &16Ω (For Direct Connection) 70V & 100V: Line (For use with LMT)
POWER SUPPLY	AC: 220-240V 50/60 Hz DC: 12V
AC POWER CONSUMPTION	220 VA
DC POWER CONSUMPTION	3 A
WEIGHT	8.800 kg (Approx)
Dimensions	W- 415 x H-142 x L-285 (Approx)