

PA AMPLIFIER AS-100-DP

PA AMPLIFIER
AS-100-DP



FEATURES & FACILITIES

- 220-240V AC & 12V DC Operation.
- 5 MIC & 2 AUX input.
- Pre amplifier & Line Output for connecting to a Booster Amplifier and for recording the Programme.
- Instant transfer to DC power (Car Battery) if AC power fails.
- Built in MP3 pleyer with Remote Control for Bluetooth, USB, MMC/SD & FM Plyer
- Delay & Repeat effects in all 5 Mics
- Bass & Treble Cut Boost type.

TECHNICAL SPECIFICATION

POWER OUTPUT	125 W Max. 100W RMS @ 10% THD
INPUT CHANNELS	5 x MIC 0.60mV/4.7kΩ 2 x AUX 100mV/470kΩ
FREQUENCY RESPONSE	50-15000Hz \pm3dB
SIGNAL TO NOISE RATIO	60dB
TONE CONTROLS	Bass \pm10db at 100Hz Treble \pm10db at 10kHz
Preamp output Line Output	200 mV/600Ω 1V/ 1kΩ
SPEAKER OUTOUT	4Ω,8Ω &16Ω (For Direct Connection) 70V & 100V: Line (For use with LMT)
POWER SUPPLY	AC: 220-240V 50/60 Hz DC: 12V
AC POWER CONSUMPTION	220 VA
DC POWER CONSUMPTION	3 A
WEIGHT	9.1kg Approx
Dimensions	W- 410 x H-120 x L-245 (Approx)