

PA AMPLIFIER AS-120-DP

PA AMPLIFIER
AS-120-DP



FEATURES & FACILITIES

- 220-240V AC & 12V DC Operation.
- 5 MIC & 2 AUX input.
- Built-in MP3 pleyer with remote control for USB, SD/MMC card reader, FM Plyer & Bluetooth.
- Line Output for connecting to a Booster Amplifier
- Preout for recording the programme. Instant transfer to DC power (Car Battery) if AC Power fails.
- Bass & Treble tone control Cut & Boost type
- Echo with Delay & Repeat Effects in all 5 Mics

CAUTION: The equipment must be earthed properly before operating to avoid electrical shock.

TECHNICAL SPECIFICATION

POWER OUTPUT	120W RMS @ 10% THD 160W MAX
INPUT CHANNELS	5 x MIC 0.60mV/4.7kΩ 2 x AUX 100mV/470kΩ
FREQUENCY RESPONSE	50- 15000Hz \pm3dB
SIGNAL TO NOISE RATIO	60dB
TONE CONTROLS:	Bass \pm10db at 100Hz Treble \pm10db at 10kHz
Preamp output Line Output	200mV/60Ω 1V/ 1kΩ
Output Taps for Speaker Matching	4Ω, 8Ω & 16Ω (For Direct Connection) 70V & 100V: Line (For use with LMT)
Power Supply	AC : 220-240 Volts 50/60 Hz DC: 12V
AC POWER CONSUMPTION	220 VA
DC POWER CONSUMPTION	3 A
NET WEIGHT	10.2kg Approx
Dimensions	W- 410 x H-120 x D-245 (Approx)