ASES SECURITY PVT. LTD.
AN ISO 9001:2015 CERTIFIED COMPANY
CIN: U32109DL 2006PTC156438

PA AMPLIFIER AS-120-DP

PA AMPLIFIER
AS-120-DP



FEATURES & FACILITIES

- 220-240V AC & 12V DC Operation.
- 5 MIC & 2 AUX input.
- Built-in MP3 plyer with remote control for USB, SD/MMC card reader, FM Plyer & Bluetooth.
- Line Output for connecting to a Booster Amplifier
- Preout for recording the programme. Instant transfer to DC power (Car Battery) if AC Power fails.
- Bass & Treble tone control Cut & Boost type
- Echo with Delay & Repeat Effects in all 5 Mics

CAUTION: The equipment must be earthed properly before operating to avoid electrical shock.

HEAD OFFICE: 301, Aggarwal Tower, L.S.C.-II, Mandawali, Patparganj, Delhi-110092.
OFFICE & WORKS : ASES House, A-2/69, Site-IV, Sahibabad Industrial Area, Ghaziabad, U.P. -201010.
•Delhi •Ghaziabad (UP) •Mumbai •Kolkata •Banglore
marcom@asesindia.com
011-22776729, 0120-4152341
www.asesindia.com

TECHNICAL SPECIFICATION

POWER OUTPUT	**120W RMS @ 10% THD** **160W MAX**
INPUT CHANNELS	**5 x MIC 0.60mV/4.7kΩ** **2 x AUX 100mV/470kΩ**
FREQUENCY RESPONSE	**50- 15000Hz ±3dB**
SIGNAL TO NOISE RATIO	**60dB**
TONE CONTROLS:	**Bass ±10db at 100Hz** **Treble ±10db at 10kHz**
Preamp output **Line Output**	**200mV/60Ω** **1V/ 1kΩ**
Output Taps for Speaker Matching	**4Ω, 8Ω & 16Ω (For Direct Connection)** **70V & 100V: Line (For use with LMT)**
Power Supply	**AC : 220-240 Volts 50/60 Hz** **DC: 12V**
AC POWER CONSUMPTION	**220 VA**
DC POWER CONSUMPTION	**3 A**
NET WEIGHT	**9.5 kg (Approx)**
Dimensions	**W- 415 x H-142 x D-285 (Approx)**