ASES SECURITY PVT. LTD.
AN ISO 9001:2015 CERTIFIED COMPANY
CIN: U32109DL 2006PTC156438

PA AMPLIFIER AS-250-DP



FEATURES & FACILITIES

- 220-240V AC & 24V dc Operation.
- 6 MIC & 2 AUX input.
- Preamplifier & Line output for connection to a booster
- Amplifier and for recording the programme.
- Instant transfer to DC power (Car Battery) if AC Power fails.
- Bass & Treble tone control Cut type
- Line input for connecting the output from any external mixier or preout SSA-300 a Booster to be used as booster power amplifier
- Bass boost defeated at driver unit position for safer operation of driver units.
- Built-IN MP3 Plyer (With remote control), for USB, SD/MMC card Reader, FM & Bluetooth Connectivity.
- Adjustable echo volume.
- 20-250 mili second delay time.

TECHNICAL SPECIFICATION

POWER OUTPUT	330W RMS @ 10% THD 350 MAX
INPUT CHANNEES	6 X MIC 0.65MV/4.7 K ohms 2 X AUX 100 mV/470 K ohms 1 X LINE 1V/50K ohms
FREQUENCY RESPONSE	50- 15000HZ+- 3db
SIGNAL TO NOISE RATIO	60 db
TONE CONTROLS:	BASS +- 10db at 100Hz TREBLE +- 10db at 100Hz
Preamp output Line Output	200 mV/600 ohms 1V/ 1kohms
Output Taps for Speaker Matching	4Ω, 8Ω ohms(For Direct Connection) 70 & 100V: Line (For use with LMT)
Power Supply	AC : 220-240 Volts 50/60 Hz DC : 24V
AC POWER CONSUMPTION	460 VA
DC POWER CONSUMPTION	6 A
ECHO DELAY TIME	30-25 MILI SECOND
NET WT	14.800 kg Approx
Dimensions	W- 430 x H-150 x D-340 (Approx)